

**A. Introduction**

- 1. Title:** Time Error Correction
- 2. Number:** BAL-004-0
- 3. Purpose:** The purpose of this standard is to ensure that Time Error Corrections are conducted in a manner that does not adversely affect the reliability of the Interconnection.
- 4. Applicability:**
  - 4.1.** Reliability Coordinators
  - 4.2.** Balancing Authorities
- 5. Effective Date:** April 1, 2005

**B. Requirements**

- R1.** Only a Reliability Coordinator shall be eligible to act as Interconnection Time Monitor. A single Reliability Coordinator in each Interconnection shall be designated by the NERC Operating Committee to serve as Interconnection Time Monitor.
- R2.** The Interconnection Time Monitor shall monitor Time Error and shall initiate or terminate corrective action orders in accordance with the NAESB Time Error Correction Procedure.
- R3.** Each Balancing Authority, when requested, shall participate in a Time Error Correction by one of the following methods:
  - R3.1.** The Balancing Authority shall offset its frequency schedule by 0.02 Hertz, leaving the Frequency Bias Setting normal; or
  - R3.2.** The Balancing Authority shall offset its Net Interchange Schedule (MW) by an amount equal to the computed bias contribution during a 0.02 Hertz Frequency Deviation (i.e. 20% of the Frequency Bias Setting).
- R4.** Any Reliability Coordinator in an Interconnection shall have the authority to request the Interconnection Time Monitor to terminate a Time Error Correction in progress, or a scheduled Time Error Correction that has not begun, for reliability considerations.
  - R4.1.** Balancing Authorities that have reliability concerns with the execution of a Time Error Correction shall notify their Reliability Coordinator and request the termination of a Time Error Correction in progress.

**C. Measures**

Not specified.

**D. Compliance**

Not specified.

**E. Regional Differences**

None identified.

**Version History**

<b>Version</b>	<b>Date</b>	<b>Action</b>	<b>Change Tracking</b>
0	April 1, 2005	Effective Date	New
0	August 8, 2005	Removed "Proposed" from Effective Date	Errata

## Standard BAL-004-0 — Time Error Correction

---

0	January 18, 2017	FERC letter order approving retirement of BAL-004-0	Retirement
---	------------------	---	------------

**\* FOR INFORMATIONAL PURPOSES ONLY \***

**Effective Date of Standard: BAL-004-0 — Time Error Correction**

**United States**

<b>Standard</b>	<b>Requirement</b>	<b>Effective Date of Standard</b>	<b>Phased In Implementation Date (if applicable)</b>	<b>Inactive Date</b>
BAL-004-0	All	06/18/2007		