

VRFs and VSLs for IRO-005-4 - Reliability Coordination — Current Day Operations

R#	VRF	Lower VSL	Moderate VSL	High VSL	Severe VSL
R1	High	The Reliability Coordinator who identified an anticipated or actual condition with Adverse Reliability Impacts within its Reliability Coordinator Area failed to issue an alert to one, but not all, impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area.	The Reliability Coordinator who identified an anticipated or actual condition with Adverse Reliability Impacts within its Reliability Coordinator Area failed to issue an alert to two, but not all, impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area.	The Reliability Coordinator who identified an anticipated or actual condition with Adverse Reliability Impacts within its Reliability Coordinator Area failed to issue an alert to three, but not all, impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area.	The Reliability Coordinator who identified an anticipated or actual condition with Adverse Reliability Impacts within its Reliability Coordinator Area failed to issue an alert to more than three impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area. OR The Reliability Coordinator who identified an anticipated or actual condition with Adverse Reliability Impacts within its Reliability Coordinator Area failed to issue an alert to all impacted Transmission Operators and Balancing Authorities in its Reliability Coordinator Area (in cases where there are less than three impacted entities).
R2	Medium	The Reliability Coordinator failed to notify one, but not all, impacted Transmission Operators, Balancing Authorities, when the transmission problem had been mitigated.	The Reliability Coordinator failed to notify two, but not all, impacted Transmission Operators, Balancing Authorities, when the transmission problem had been mitigated.	The Reliability Coordinator failed to notify three, but not all, impacted Transmission Operators, Balancing Authorities, when the transmission problem had been mitigated.	The Reliability Coordinator failed to notify more than three impacted Transmission Operators, Balancing Authorities, when the transmission problem had been mitigated. OR The Reliability Coordinator failed

VRFs and VSLs for IRO-005-4 - Reliability Coordination — Current Day Operations

R#	VRF	Lower VSL	Moderate VSL	High VSL	Severe VSL
					to notify more all impacted Transmission Operators, Balancing Authorities, when the transmission problem had been mitigated (in cases where there are less than three impacted entities).